

N- and P-Channel 40 V (D-S) 175 °C MOSFET

DESCRIPTION


The attached SPICE model describes the typical electrical characteristics of the n- and p-channel vertical DMOS. The sub-circuit model is extracted and optimized over the -55 °C to +125 °C temperature ranges under the pulsed 0 V to 10 V gate drive. The saturated output impedance is best fit at the gate bias near the threshold voltage.

A novel gate-to-drain feedback capacitance network is used to model the gate charge characteristics while avoiding convergence difficulties of the switched C_{gd} model. All model parameter values are optimized to provide a best fit to the measured electrical data and are not intended as an exact physical interpretation of the device.

CHARACTERISTICS

- N- and p-channel vertical DMOS
- Macro model (Sub-circuit model)
- Level 3 MOS
- Apply for both linear and switching application
- Accurate over the -55 °C to +125 °C temperature range
- Model the gate charge

SUBCIRCUIT MODEL SCHEMATIC



Note

- This document is intended as a SPICE modeling guideline and does not constitute a commercial product datasheet. Designers should refer to the appropriate datasheet of the same number for guaranteed specification limits.



SPECIFICATIONS (T _J = 25 °C, unless otherwise noted)						
PARAMETER	SYMBOL	TEST CONDITIONS		SIMULATED DATA	MEASURED DATA	UNIT
Static						
Gate-Source Threshold Voltage	V _{GS(th)}	V _{DS} = V _{GS} , I _D = 250 μA	N-Ch	2	-	V
		V _{DS} = V _{GS} , I _D = -250 μA	P-Ch	2	-	
Drain-Source On-State Resistance ^a	R _{DS(on)}	V _{GS} = 10 V, I _D = 9.8 A	N-Ch	0.0074	0.0077	Ω
		V _{GS} = -10 V, I _D = -6 A	P-Ch	0.0200	0.0220	
		V _{GS} = 4.5 V, I _D = 8.9 A	N-Ch	0.0095	0.0094	
		V _{GS} = -4.5 V, I _D = -4.7 A	P-Ch	0.0350	0.0360	
Forward Transconductance ^a	g _{fs}	V _{DS} = 15 V, I _D = 9.8 A	N-Ch	50	65	S
		V _{DS} = -15 V, I _D = -6 A	P-Ch	15	16	
Diode Forward Voltage ^a	V _{SD}	I _S = 6.5 A, V _{GS} = 0 V	N-Ch	0.79	0.79	V
		I _S = -3.4 A, V _{GS} = 0 V	P-Ch	-0.78	-0.78	
Dynamic ^b						
Input Capacitance	C _{iss}	N-Channel V _{DS} = 20 V, V _{GS} = 0 V, f = 1 MHz P-Channel V _{DS} = -20 V, V _{GS} = 0 V, f = 1 MHz	N-Ch	1500	1474	pF
Output Capacitance	C _{oss}		P-Ch	1320	1302	
			N-Ch	223	218	
Reverse Transfer Capacitance	C _{rss}		P-Ch	223	222	
			N-Ch	91	89	
			P-Ch	154	154	
Total Gate Charge	Q _g	N-Channel V _{DS} = 20 V, V _{GS} = 10 V, I _D = 10 A P-Channel V _{DS} = -20 V, V _{GS} = -10 V, I _D = -10 A	N-Ch	24	25.5	nC
Gate-Source Charge	Q _{gs}		P-Ch	27	30.2	
			N-Ch	4.4	4.4	
Gate-Drain Charge	Q _{gd}		P-Ch	4.1	4.1	
			N-Ch	4.3	4.3	
			P-Ch	7.4	7.4	







Notes

- a. Pulse test; pulse width $\leq 300\ \mu\text{s}$, duty cycle $\leq 2\ \%$.
b. Guaranteed by design, not subject to production testing.



COMPARISON OF MODEL WITH MEASURED DATA $T_J = 25\text{ }^{\circ}\text{C}$, unless otherwise noted

N-Channel MOSFET









Note

- Dots and squares represent measured data.



COMPARISON OF MODEL WITH MEASURED DATA $T_J = 25\text{ }^{\circ}\text{C}$, unless otherwise noted

P-Channel MOSFET



Note

- Dots and squares represent measured data.

Copyright: Vishay Intertechnology, Inc.