



## High-Speed SSRs Target Test and Measurement Applications



### FEATURES

- Maximum  $t_{ON}$ ,  $t_{OFF}$ : 800  $\mu$ s
- Maximum  $R_{ON}$ : 0.25  $\Omega$
- Load current: 1 A
- Load voltage: 60 V
- Trigger current ( $I_F$ ): 1 mA
- Encased in a DIP-6 package
- Pure tin leads


### BENEFITS

- Maximum  $t_{ON}$ ,  $t_{OFF}$  of 800  $\mu$ s reduces time required for powering up the diagnostic routine in test and measurement applications
- Maximum  $R_{ON}$  of 0.25  $\Omega$  is optimal for applications requiring low power consumption and heat dissipation
- Low input trigger current allows direct interface with digital logic
- Crosses to NEC PS710A and Clare LCA710
- Component in accordance to RoHS 2002/95/EC and WEEE 2002/96/EC

### RESOURCES

- Datasheet: <http://www.vishay.com/doc?81646>
- Solid State Relays Portfolio: <http://www.vishay.com/solid-state-relays/>
- For technical questions contact: [optocouplersanswer@vishay.com](mailto:optocouplersanswer@vishay.com)

One of the World's Largest Manufacturers of  
Discrete Semiconductors and Passive Components



**APPLICATIONS**






- Automated test equipment
- Board testers
- Medical and instrumentation
- Industrial Controls

**SAFETY**

- Certified by key international safety regulatory agencies such as UL, CUL, and VDE

The VO14642A is the highest-speed SSR in its class. A fast  $T_{ON}/T_{OFF}$  of 800  $\mu$ s maximum facilitates test and measurement applications while the low  $R_{ON}$  of 0.25  $\Omega$  helps in applications needing low power consumption and heat dissipation.

The VO14642A can be configured for AC/DC or DC-only operation. In the AC/DC configuration the maximum  $R_{ON}$  is 0.25  $\Omega$  and the maximum peak load current is 3.6 A. In the DC-only configuration the maximum  $R_{ON}$  is 0.07  $\Omega$  and the maximum peak load current is 2 A.

**AC/DC Configuration**

**DC Only Configuration**


| Part Number  | Package | Packing     | $R_{ON} (\Omega)$ | $I_{LOAD} (A)$ |
|--------------|---------|-------------|-------------------|----------------|
| VO14642AT    | DIP-6   | Tubes       | 0.25              | 2              |
| VO14642AABTR | DIP-6   | Tape & Reel | 0.25              | 2              |